

STUDER

PROFESSIONAL AUDIO EQUIPMENT

Service Information

SERVICE INFORMATION
SI 37/78 E

Conversion of a TLS 2000 into a type with built-in Generator

Valid for: TLS 2000 MK II installed in A80/VU only.

This conversion can only be done on TLS 2000 MK II versions.
The following alterations have to be done:

- Replace of boards which contain soft-ware:

1.228.480

1.228.481 soft-ware (replace complete board only)

1.228.482

1.228.483 replace with 1.228.488

- Wiring on back panel rack

	Location	Pin	-	Location	Pin
disconnect connection	11	25A	-	11	25C
additional connections	01	05C	-	11	25A
	01	06C	-	11	25C