

# Enable wifi after suspend-resume

## To enable wifi after resume, when it is turned off

Create a systemd service “root-resume.service” in /etc/systemd/system with content:

```
[Unit]
Description=Local system resume actions
After=suspend.target

[Service]
Type=simple
ExecStart=/usr/bin/nmcli radio wifi on

[Install]
WantedBy=suspend.target
```

and enable the newly created service:

```
# systemctl enable root-resume.service
```

---

Revision #3

Created 2026-04-01 17:15:33 CEST by Philip

Updated 2026-04-13 19:27:21 CEST by Philip