

Asus f2a85-v

CPU Chipset Geheugen Grafische Ondersteuning Multi-GPU Uitbreidingsslots Opslag LAN Audio
AMD Socket FM2 Athlon™ /A- Series Processors Supports CPU up to 4 cores Supports AMD® Turbo
Core 3.0 Technology AMD A85X FCH(Hudson D4) 4 x DIMM, Max. 64GB, DDR3
2400(O.C.)/2250(O.C.)/2200(O.C.)/2133(O.C.)/2000(O.C.)/1866/1600/1333/1 066 MHz Non-ECC, Un-
buffered Memory Dual Channel Memory Architecture

- Refer to www.asus.com or this user manual for the Memory QVL (Qualified

Vendors Lists). Support AMD Memory Profile (AMP) memory

- Due to OS limitation, when installing total memory of 4GB capacity or more,

Windows® 32-bit operation system may only recognize less than 3GB. Install a 64-bit
Windows® OS when you want to install 4GB or more memory on the motherboard.

- The Max. 64GB memory capacity can be supported with DIMMs of 16GB

(or above). ASUS will update QVL once the DIMMs are available on the market. Integrated AMD
Radeon™ HD 7000 Series Graphics in Aseries APU Multi-VGA output support : HDMI/DVI/RGB ports -
Supports HDMI with max. resolution 1920 x 1080 @ 60 Hz - Supports DVI with max. resolution 2560
x 1600 @ 60 Hz - Supports RGB with max. resolution 1920 x 1600 @ 60 Hz Maximum shared
memory of 2048 MB AMD® Dual Graphics technology support * Supports DirectX 11 Supports AMD
CrossFire™ Technology 2 x PCIe 2.0 x16 (x16/x4) 2 x PCIe 2.0 x1 3 x PCI AMD A85X FCH(Hudson
D4) chipset : 7 x SATA 6Gb/s ports (gray), gray 1 x SATA 6.0 Gb/s ports, red Support Raid 0, 1, 5,
10, JBOD Qualcomm Atheros, 1 x Gigabit LAN Controller Realtek® ALC887 8-Channel High
Definition Audio CODEC - Supports : Jack-detection, Multi-streaming, Front Panel Jack-retasking
Audio Feature : - Optical S/PDIF out port(s) at back panel

Revision #3

Created 2026-04-01 17:14:15 CEST by Philip

Updated 2026-04-13 19:28:41 CEST by Philip